











# Jackery Explorer 2000 Pro

EAN : 0190074000096



- |  |   |
|--|---|
|  Refrigerator<br><b>3.3H</b> (520W)     |  Coffee Maker<br><b>3H</b> (1150W)     |
|  Air Conditioner<br><b>2H</b> (1150W)   |  Electric Grill<br><b>1.1H</b> (1600W) |
|  Microwave<br><b>96Min</b> (1160W)      |  Hot Plate<br><b>48Min</b> (2300W)     |
|  Air Compressor<br><b>86Min</b> (1200W) |  Electric Hammer<br><b>2H</b> (800W)   |

SPECIFICATION	
Capacity	2160Wh (43.2V, 50Ah)
Continuous Output	2200W
Peak Output	4400W
Battery Type	Li-ion NMC
Battery Lifecycles	≥1000 cycles to 80%+ capacity
Product Weight	19.5 kg
Dimension	384 x 269 x 308 mm
Output Ports	AC Output(x2): 230V, 2200W (4400W Peak) USB-A Output(x2): Quick Charge 3.0, 18W Max. 5–6V, 3A / 6–9V, 2A / 9–12V, 1.5A USB-C Output(x2): 100W Max, (5V/3A, 9V/3A, 12V3A, 15V/3A, 20V/5A) Car Port(x1): 12V, 10A
Input Ports	AC Input: 230V, 50Hz, 10A Max DC Input: 11V-17.5V, 8A Max, double to 8A Max 17.5V-60V, 12A, double to 24A/1400W Max

WHAT'S IN THE BOX
 1* Jackery Explorer 2000 Pro
 1* Car Charge Cable
 1* AC Charge Cable
 2* DC7909 To 8020 Adapter
 1* User Manual

PACKAGE & RECHARGING TIME TO 100%	
Box Size	428*394*318 mm
Weight with Box	20.23 kg
Qty / Carton	1 pcs/carton
GW	22.77 kg
Carton Size	438*328*396 mm
Charged with AC Adapter	2 hours
Charged with 12V Car Outlet	24 hours
Charged with 6*SolarSaga 200	2.5 hours
Charged with 4*SolarSaga 200	4 hours
Charged with 2*SolarSaga 200	7.5 hours

RECOMMENDED COMBO
 Solar Generator 2000 Pro 400W (Explorer 2000 Pro+2*SolarSaga 200)
 Solar Generator 2000 Pro 1200W (Explorer 2000 Pro+6*SolarSaga 200)