






Jackery Explorer 1000 Pro

EAN : 0190074000324




-  Portable Refrigerator
38H (60W)
-  Coffee Maker
1.5H (550W)
-  Blender
2.5H (300W max)
-  Ice Shaver
1.2H (700W)
-  Microwave
1.2H (700W)
-  Space Heater
2.5H (350W)
-  Air Fryer
0.9H (1000W)
-  Electric Drill
2H (900W)

SPECIFICATION	
Capacity	1002Wh (43.2V/23.2Ah)
Continuous Output	1000W
Peak Output	2000W
Battery Type	Li-ion NMC
Battery Lifecycles	≥1000 cycles to 80%+ capacity
Product Weight	11.5 kg
Dimension	340 x 262 x 256 mm
Output Ports	AC Output(x2): 230V, 1000W (2000W Peak) USB-A Output(x2): Quick Charge 3.0, 18W Max. 5–6V, 3A / 6–9V, 2A / 9–12V, 1.5A USB-C Output(x2): 100W Max, (5V/3A,9V/3A,12V3A, 15V/3A,20V/5A) Car Port(x1): 12V,10A
Input Ports	AC Input: 230V, 50Hz, 10A Max DC Input: 17.5V-60V, 11A Max, double to 22A/800W max Car charge 12~17.5V/8A, double to 16A


WHAT'S IN THE BOX
 1* Jackery Explorer 1000 Pro
 1* Car Charge Cable
 1* AC Charge Cable
 2* DC7909 To 8020 Adapter
 1* User Manual

PACKAGE & RECHARGING TIME TO 100%	
Box Size	375*296*329 mm
Weight with Box	13.06 kg
Qty / Carton	1pcs/carton
GW	14.13 kg
Carton Size	395*315*350 mm
Charged with AC Adapter	1.8 hours
Charged with 12V Car Outlet	12.2 hours
Charged with 2*SolarSaga 80	9 hours
Charged with 4*SolarSaga 200	1.8 hours

RECOMMENDED COMBO



Solar Generator 1000 Pro 160W
(Explorer 1000 Pro+2*SolarSaga 80)



Solar Generator 1000 Pro 800W
(Explorer 1000 Pro+4*SolarSaga 200)