

ROTEL

TUNER FM/DAB+

T11



Syntonisation DAB+



Capacité RDS (décodage
d'informations routières)
pour la radiodiffusion en FM



Télécommande incluse

Rotel fabrique des tuners de haute qualité depuis les années 1960. Et l'un des tout derniers ajouts à cette longue lignée, c'est le tuner FM/DAB+ T11. Il offre de très larges possibilités d'écoute, avec un accès facile aussi bien aux stations de radio analogiques en FM qu'aux nouveaux services numériques en DAB+.

Comme le T14, le T11 dispose de la capacité de mémoriser et de rappeler facilement jusqu'à 30 stations prééglées, à la fois en FM ou en DAB+. Autre fonction utile, et commune à l'ensemble des produits de la gamme 14, c'est la possibilité de réduire la luminosité de l'écran d'affichage ainsi que celle de la LED de mise sous tension, pour un meilleur confort visuel dans toutes les ambiances d'éclairage.

Rotel tuners provide
a wealth of high
quality listening
choices.
See more at

rotel.com



TUNER FM/DAB+

T11



SPECIFICATIONS

FM Tuner

Usable Sensitivity	22.2 dBf
50dB Quieting Sensitivity	27.2 dBf (mono)
Signal to Noise Ratio	
Mono	63 dBf (at 65 dBf)
Stereo	60 dBf (at 65 dBf)
Harmonic Distortion	
Mono	0.2% (at 65 dBf)
Stereo	0.3% (at 65 dBf)
Frequency Response	10Hz - 15kHz, $\pm$ 3dB
Stereo Separation (100Hz/1kHz)	40 dB / 37 dB
Analog Output	1.0 V
Antenna Input	75 Ohms F connector

DAB Tuner

Sensitivity	-80 dBm
Tuning Range	Band III (174 - 240MHz)
Audio Data Rate	224kbps (Max)
Frequency Response	20 - 20kHz, $\pm$ 1.0 dB
Analog Output	2.1V at 0 dBFS
Antenna Input	75 Ohms F connector

General

Power Requirements (AC)	
Europe	230V, 50Hz
USA	120V, 60Hz
Power Consumption	10 watts
Standby Power Consumption	< 0.5 watts
Finishes	Silver and Black
Dimensions (W x H x D)	430 x 73 x 331mm 17" x 2 7/8" x 13"
Front Panel Height	60mm, 2 3/8"
Weight (net)	4.3 kg, 9.5 lb

Rotel tuners provide a wealth of high quality listening choices. See more at

rotel.com

